


# Diesel Generator Set

## Model DQHAB 60 Hz

### EPA Emissions

**300 kW, 375 kVA Standby**  
**270 kW, 338 kVA Prime**



## Description

Cummins Power Generation commercial generator sets are fully integrated power generation systems providing optimum performance, reliability, and versatility for stationary standby or prime power applications.

A primary feature is strong motor-starting capability and fast recovery from transient load changes. The torque-matched system includes a heavy-duty Cummins 4-cycle diesel engine, an AC alternator with high motor-starting kVA capacity, and an electronic voltage regulator with three phase sensing for precise regulation under steady-state or transient loads. The GenSet accepts 100% of the nameplate standby rating in one step, in compliance with NFPA 110 Level 1 requirements.

The standard PowerCommand® digital electronic control is an integrated system that combines engine and alternator controls for high reliability and optimum GenSet performance.

Optional weather-protective enclosures and coolant heaters allow generators to perform in outdoor weather operating conditions. Environmental concerns are addressed by low exhaust emission engines, sound-attenuated enclosures, exhaust silencers, and dual-wall fuel tanks. A wide range of options, accessories, and services are available, allowing configuration to your specific power generation needs.

Every production unit is factory tested at rated load and power factor. This testing includes demonstration of rated power and single-step rated load pickup. Cummins Power Generation manufacturing facilities are registered to ISO9001 quality standards, emphasizing our commitment to high quality in the design, manufacture, and support of our products. The generator set is CSA certified (pending) and is available as UL 2200 Listed. The PowerCommand control is UL 508 Listed.

All Cummins Power Generation systems are backed by a comprehensive warranty program and supported by a worldwide network of 170 distributors and service branches to assist with warranty, service, parts, and planned maintenance support.

## Features

**UL Listed Generator Set** - The complete generator set assembly is available as UL 2200 Listed.

**Low Exhaust Emissions** - Engine certified to U.S. EPA Nonroad source emissions standards, 40 CFR 89, Tier 3.

**Cummins Heavy-Duty Engine** - Rugged 4-cycle industrial diesel engine delivers reliable power, low emissions, and fast response to load changes.

**Alternator** - Several alternator sizes offer selectable motor starting capability with low reactance 2/3 pitch windings; low waveform distortion with non-linear loads, fault clearing short-circuit capability, and class H insulation. The alternator electrical insulation system is UL1446 Recognized.

**Permanent Magnet Generator (PMG)** - Offers enhanced motor starting and fault clearing short circuit capability.

**Control System** - The PowerCommand electronic control is standard equipment and provides total genset system integration, including automatic remote starting/stopping, precise frequency and voltage regulation, alarm and status message display, AmpSentry™ protection, output metering, auto-shutdown at fault detection, and NFPA 110 Level 1 compliance. PowerCommand control is Listed to UL508.

**Cooling System** - Provides reliable running at the rated power level, at up to 52°C ambient temperature.

**Integral Vibration Isolation** - Robust skid base supports the engine, alternator, and radiator on isolators, minimizing transmitted vibration.

**E-Coat Finish** - Dual electro-deposition paint system provides high resistance to scratches, corrosion, or fading.

**Enclosures** - Optional weather-protective and sound-attenuated enclosures are available.

**Fuel Tanks** - Dual wall sub-base fuel tanks are also offered.

**Certifications** - Generator sets are designed, manufactured, tested, and certified to relevant UL, NFPA, ISO, IEC, and CSA standards.

**Warranty and Service** - Backed by a comprehensive warranty and worldwide distributor network.

# Generator Set

The general specifications provide representative configuration details. Consult the outline drawing for installation design.

## Specifications – General

See outline drawing 500-4645 for installation design specifications.

<b>Unit Width, in (mm)</b>	60 (1524)
<b>Unit Height, in (mm)</b>	71 (1803)
<b>Unit Length, in (mm)</b>	136 (3453)
<b>Unit Dry Weight, lb (kg)</b>	5900 (2676)
<b>Unit Wet Weight, lb (kg)</b>	6090 (2762)
<b>Rated Speed, rpm</b>	1800
<b>Voltage Regulation, No Load to Full Load</b>	±0.5%
<b>Random Voltage Variation</b>	±0.5%
<b>Frequency Regulation</b>	Isochronous
<b>Random Frequency Variation</b>	±0.5%
<b>Radio Frequency Interference</b>	IEC 801.2, Level 4 Electrostatic Discharge IEC 801.3, Level 3 Radiated Susceptibility IEC 801.4, Level 4 Electrical Fast Transients IEC 801.5, Level 5 Voltage Surge Immunity MIL STD 461C, Part 9 Radiated Emissions (EMI)

Cooling	Standby	Prime
Fan Load, HP (kW)	27 (20.1)	27 (20.1)
Coolant Capacity with radiator, US Gal (L)	8.9 (33.7)	8.9 (33.7)
Coolant Flow Rate, Gal/min (L/min)	140 (529.9)	140 (529.9)
Heat Rejection To Coolant, Btu/min (MJ/min)	10524 (11.10)	8344 (8.80)
Heat Radiated To Room, Btu/min (MJ/min)	2000 (2.11)	1789 (1.88)
Maximum Coolant Friction Head, psi (kPa)	10 (68.9)	10 (68.9)
Maximum Coolant Static Head, ft (m)	46 (14)	46 (14)

Air		
Combustion Air, scfm (m <sup>3</sup> /min)	866.82 (24.54)	814.59 (23.06)
Alternator Cooling Air, scfm (m <sup>3</sup> /min)	1240.0 (35.1)	1240.0 (35.1)
Radiator Cooling Air, scfm (m <sup>3</sup> /min)	25000.0 (707.5)	25000.0 (707.5)
Max. Static Restriction, in H <sub>2</sub> O (Pa)	0.50 (124.50)	0.50 (124.50)

## Rating Definitions

**Standby Rating based on:** Applicable for supplying emergency power for the duration of normal power interruption. No sustained overload capability is available for this rating. (Equivalent to Fuel Stop Power in accordance with ISO3046, AS2789, DIN6271 and BS5514). Nominally rated.

**Prime (Unlimited Running Time) Rating based on:** Applicable for supplying power in lieu of commercially purchased power. Prime power is the maximum power available at a variable load for an unlimited number of hours. A 10% overload capability is available for limited time. (Equivalent to Prime Power in accordance with ISO8528 and Overload Power in accordance with ISO3046, AS2789, DIN6271, and BS5514). This rating is not applicable to all generator set models.

## Site Derating Factors

**Standby engine power** available up to 875 m (2870 ft) at ambient temperature up to 40°C (104°F) or up to 400 m (1312 ft) at ambient temperatures up to 50°C (122°F). Engine power derate for altitude and temperature conditions outside those listed: derate 4% per 300 m (984 ft), and 10% per 10°C (18°F).

**Prime engine power** available up to 1000 m (3280 ft) at ambient temperature up to 40°C (104°F) or up to 325 m (1066 ft) at ambient temperatures up to 50°C (122°F). Engine power derate for altitude and temperature conditions outside those listed: derate 4% per 300 m (984 ft), and 10% per 10°C (18°F).

# Engine

Cummins heavy duty diesel engines use advanced combustion technology for reliable and stable power, low emissions, and fast response to sudden load changes.

Electronic governing provides precise speed regulation, especially useful for applications requiring constant (isochronous) frequency regulation such as Uninterruptible Power Supply (UPS) systems, non-linear loads, or sensitive electronic loads. Optional coolant heaters are recommended for all emergency standby installations or for any application requiring fast load acceptance after start-up.

## Specifications – Engine

<b>Base Engine</b>	Cummins, Inc Model QSM11-G4, Turbocharged, EGR, and CAC, diesel-fueled
<b>Displacement in<sup>3</sup> (L)</b>	661.0 (10.8)
<b>Overspeed Limit, rpm</b>	2100 ±50
<b>Regenerative Power, kW</b>	30.6
<b>Cylinder Block Configuration</b>	Cast iron, In-line 6 cylinder
<b>Battery Capacity</b>	550 amps at ambient temperature of 32°F (-0°C) and above
<b>Battery Charging Alternator</b>	70 amps
<b>Starting Voltage</b>	24-volt, negative ground
<b>Lube Oil Filter Types</b>	Single spin-on, combination full flow and bypass filters
<b>Standard Cooling System</b>	125°F (52°C) ambient radiator

<b>Power Output</b>		<b>Standby</b>				<b>Prime</b>			
Gross Engine Power Output, bhp (kWm)		470 (350)				427 (318)			
BMEP at Rated Load, psi (kPa)		314 (2165)				285 (1965)			
Bore, in. (mm)		4.92 (125)				4.92 (125)			
Stroke, in. (mm)		5.79 (147.1)				5.79 (147.1)			
Piston Speed, ft/min (m/s)		17.37 (0.88)				17.37 (0.88)			
Compression Ratio		17:1				17:1			
Lube Oil Capacity, qt. (L)		38.8 (36.72)				38.8 (36.72)			
<b>Fuel Flow</b>									
Fuel Flow at Rated Load, US Gal/hr (L/hr)		75 (284)				75 (284)			
Maximum Inlet Restriction, in. Hg (mm Hg)		8 (204)				8 (204)			
Maximum Return Restriction, in. Hg (mm Hg)		8 (204)				8 (204)			
<b>Air Cleaner</b>									
Maximum Air Cleaner Restriction, in. H <sub>2</sub> O (kPa)		25.0 (6.2)				25.0 (6.2)			
<b>Exhaust</b>									
Exhaust Flow at Rated Load, cfm (m <sup>3</sup> /min)		2345 (66.4)				2135 (60.46)			
Exhaust Temperature, °F (°C)		1011 (543.8)				955 (513)			
Max Back Pressure, in. H <sub>2</sub> O (kPa)		40.8 (10.15)				34.0 (8.46)			
<b>Fuel System</b>		Direct injection, number 2 diesel fuel; fuel filter (with water separator); automatic electric fuel shutoff							
<b>Fuel Consumption</b>		<b>Standby</b>				<b>Prime</b>			
<b>60 Hz Ratings, kW (kVA)</b>		<b>300 (375)</b>				<b>270 (338)</b>			
	Load	1/4	1/2	3/4	Full	1/4	1/2	3/4	Full
	US Gal/hr	6.67	11.57	17.12	23.15	6.28	10.66	15.51	20.66
	L/hr	25.25	43.80	64.81	87.63	23.77	40.35	58.71	78.21

## Alternator

Several alternators are available for application flexibility based on the required motor-starting kVA and other requirements. Larger alternator sizes have lower temperature rise for longer life of the alternator insulation system. In addition, larger alternator sizes can provide a cost-effective use of engine power in across-the-line motor-starting applications and can be used to minimize voltage waveform distortion caused by non-linear loads.

Single-bearing alternators couple directly to the engine flywheel with flexible discs for drivetrain reliability and durability. No gear reducers or speed changers are used. Two-thirds pitch windings eliminate third-order harmonic content of the AC voltage waveform and provide the standardization desired for paralleling of generator sets. The standard excitation system is a PMG excited system.

## Alternator Application Notes

**Separately Excited Permanent Magnet Generator (PMG) System** - This standard system uses an integral PMG to supply power to the voltage regulator. A PMG system generally has better motor-starting performance, lower voltage dip upon load application, and better immunity from problems with harmonics in the main alternator output induced by non-linear loads. This system provides improved performance over self-excited regulators in applications that have large transient loads, sensitive electronic loads (especially UPS applications), harmonic content, or that require sustained short-circuit current (sustained 3-phase short circuit current at approximately 3 times rated for 10 seconds).

**Alternator Sizes** - On any given model, various alternator sizes are available to meet individual application needs. Alternator sizes are differentiated by maximum winding temperature rise, at the generator set standby or prime rating, when operated in a 40°C ambient environment. Available temperature rises range from 80°C to 150°C. Not all temperature rise selections are available on all models. Lower temperature rise is accomplished using larger alternators at lower current density. Lower temperature rise alternators have higher motor-starting kVA, lower voltage dip upon load application, and they are generally recommended to limit voltage distortion and heating due to harmonics induced by non-linear loads.

**Alternator Space Heater** - is recommended to inhibit condensation.

## Available Output Voltages

### Three Phase Reconnectable

- 110/190
- 115/200
- 115/230
- 120/208
- 127/220
- 139/240
- 120/240
- 220/380
- 230/400
- 240/416
- 254/440
- 277/480

### Three Phase Non-Reconnectable

- 347/600

# Specifications – Alternator


<b>Design</b>	Brushless, 4 pole, drip proof revolving field
<b>Stator</b>	2/3 pitch
<b>Rotor</b>	Direct coupled by flexible disc
<b>Insulation System</b>	Class H per NEMA MG1-1.65
<b>Standard Temperature Rise</b>	125°C Standby, 105°C @ Prime
<b>Exciter Type</b>	Permanent Magnet Generator (PMG)
<b>Phase Rotation</b>	A (U), B (V), C (W)
<b>Alternator Cooling</b>	Direct drive centrifugal blower
<b>AC Waveform Total Harmonic Distortion</b>	<5% total no load to full linear load <3% for any single harmonic <50 per NEMA MG1-22.43
<b>Telephone Influence Factor (TIF)</b>	<3
<b>Telephone Harmonic Factor (THF)</b>	<3

Three Phase Table <sup>1</sup>		80° C	105° C	105° C	125° C	125° C	125° C	125° C					
Feature Code		B302	B256	B301	B258	B252	B246	B300					
Alternator Data Sheet Number		342	342	342	342	341	340	340					
Voltage Ranges		347/600	120/208 Thru 139/240 240/416 Thru 277/480	347/600	110/190 Thru 139/240 220/380 Thru 277/480	120/208 Thru 139/240 240/416 Thru 277/480	277/480	347/600					
Surge kW		321	316	321	317	318	318	318					
Motor Starting kVA (at 90% sustained voltage)	PMG	1372	1372	1372	1372	1210	1028	1028					
Full Load Current - Amps at Standby Rating		<u>120/208</u> 1042	<u>127/220</u> 985	<u>139/240</u> 903	<u>220/380</u> 570	<u>240/416</u> 521	<u>254/440</u> 492	<u>277/480</u> 452	<u>347/600</u> 361				

**Notes:**

Single phase power can be taken from a three phase generator set at up to 40% of the generator set nameplate kW rating at unity power factor.

# Control System

 <p>The image shows a PowerCommand control panel with a digital display, several analog meters, and a large red emergency stop button. The panel is housed in a dark enclosure with various labels and indicators.</p>	<p><b>PowerCommand Control with AmpSentry™ Protection (PCC2100 CAN)</b></p> <ul style="list-style-type: none"> <li>• The PowerCommand Control is an integrated generator set control system providing governing, voltage regulation, engine protection, and operator interface functions.</li> <li>• PowerCommand Controls include integral UL Listed AmpSentry protection. AmpSentry provides a full range of alternator protection functions that are matched to the alternator provided.</li> <li>• Controls provided include Battery monitoring and testing features.</li> <li>• Integral PCCNet interface, to allow high speed network interconnections to remote input/output (I/O) and annunciator modules.</li> <li>• InPower PC-based service tool available for detailed diagnostics.</li> <li>• NEMA 3R enclosure.</li> <li>• Suitable for operation in ambient temperatures from -40C to +70C, and altitudes to 13,000 feet (5000 meters).</li> <li>• Prototype tested; UL, CSA, and CE compliant.</li> </ul>	
<p><b>AmpSentry AC Protection</b></p> <ul style="list-style-type: none"> <li>• Overcurrent and short circuit shutdown</li> <li>• Overcurrent warning</li> <li>• Single &amp; 3-phase fault regulation</li> <li>• Over and under voltage shutdown</li> <li>• Over and under frequency shutdown</li> <li>• Overload warning with alarm contact</li> <li>• Reverse power and reverse Var shutdown</li> <li>• Excitation fault</li> </ul>	<p><b>Engine Protection</b></p> <ul style="list-style-type: none"> <li>• Overspeed shutdown</li> <li>• Low oil pressure warning and shutdown</li> <li>• High coolant temperature warning and shutdown</li> <li>• High oil temperature warning (optional)</li> <li>• Low coolant level warning or shutdown</li> <li>• Low coolant temperature warning</li> <li>• High and low battery voltage warning</li> <li>• Weak battery warning</li> <li>• Dead battery shutdown</li> <li>• Fail to start (overcrank) shutdown</li> <li>• Fail to crank shutdown</li> <li>• Redundant start disconnect</li> <li>• Cranking lockout</li> <li>• Sensor failure indication</li> </ul>	<p><b>Operator Interface</b></p> <ul style="list-style-type: none"> <li>• OFF/MANUAL/AUTO mode switch</li> <li>• MANUAL RUN/STOP switch</li> <li>• Panel lamp test switch</li> <li>• Emergency Stop switch</li> <li>• Alpha-numeric display with pushbutton access, for viewing engine and alternator data and providing setup, controls, and adjustments</li> <li>• LED lamps indicating genset running, not in auto, common warning, common shutdown</li> <li>• (5) configurable LED lamps</li> <li>• LED Bargraph AC data display (optional)</li> </ul>
<p><b>Alternator Data</b></p> <ul style="list-style-type: none"> <li>• Line-to-line and line-to-neutral AC volts</li> <li>• 3-phase AC current</li> <li>• Frequency</li> <li>• Total and individual phase kW and kVA</li> </ul>	<p><b>Engine Data</b></p> <ul style="list-style-type: none"> <li>• DC voltage</li> <li>• Lube oil pressure</li> <li>• Coolant temperature</li> <li>• Lube oil temperature (optional)</li> </ul>	<p><b>Other Data</b></p> <ul style="list-style-type: none"> <li>• Genset model data</li> <li>• Start attempts, starts, running hours</li> <li>• KW hours (total and since reset)</li> <li>• Fault history</li> <li>• Load profile (hours less than 30% and hours more than 90% load)</li> <li>• System data display (optional with network and other PowerCommand gensets or transfer switches)</li> </ul>
<p><b>Governing</b></p> <ul style="list-style-type: none"> <li>• Digital electronic isochronous governor</li> <li>• CAN data-link interface to full authority electronic engine control</li> </ul>	<p><b>Voltage Regulation</b></p> <ul style="list-style-type: none"> <li>• Integrated digital electronic voltage regulator</li> <li>• 3-phase line to neutral sensing</li> <li>• PMG (Optional)</li> <li>• Single and three phase fault regulation</li> <li>• Configurable torque matching</li> </ul>	<p><b>Control Functions</b></p> <ul style="list-style-type: none"> <li>• Data logging on faults</li> <li>• Fault simulation (requires InPower)</li> <li>• Time delay start and cooldown</li> <li>• Cycle cranking</li> <li>• (4) Configurable customer inputs</li> <li>• (4) Configurable customer outputs</li> <li>• PCCNet Interface, network interconnections to I/O modules, annunciators, and other equipment</li> </ul>
<p><b>Options</b></p>		
<ul style="list-style-type: none"> <li><input type="checkbox"/> Analog AC Meter Display</li> <li><input type="checkbox"/> Thermostatically-Controlled Space Heater</li> </ul>	<ul style="list-style-type: none"> <li><input type="checkbox"/> Key-type mode switch</li> <li><input type="checkbox"/> Engine oil temperature sensing and alarm</li> <li><input type="checkbox"/> Auxiliary Relays (3)</li> </ul>	<ul style="list-style-type: none"> <li><input type="checkbox"/> Echelon LonWorks interface</li> <li><input type="checkbox"/> LonWorks network input and output module(s) (loose) (8) Configurable inputs and (16) outputs</li> <li><input type="checkbox"/> Remote network annunciator (loose) - LonWorks</li> </ul>

## Generator Set Options

### Engine

- 240 V, 300 W lube oil heater
- 480 V, 300 W lube oil heater
- 208/240-480 V, 4500 W coolant heater
- 208/240-480 V, 6500 W coolant heater
- Heavy Duty Air Cleaner

### Fuel System

- 270 Gallon ( L) sub-base tank
- 300 Gallon ( L) sub-base tank
- 400 Gallon ( L) sub-base tank
- 500 Gallon ( L) sub-base tank
- 600 Gallon ( L) sub-base tank
- 660 Gallon ( L) sub-base tank
- 850 Gallon ( L) sub-base tank
- 1700 Gallon ( L) sub-base tank
- Day Tank with pump control

### Alternator

- 80°C Rise Alternator
- 105°C rise alternator
- 125°C rise alternator
- 120 V, 100 W anti-condensation heater
- 240 V, 100 W anti-condensation heater

### Control Panel

- 120 V, 30 W control anti-condensation heater
- 240 V, 30 W control anti-condensation heater
- Exhaust pyrometer
- Ground fault indication
- Remote fault signal package
- Run relay package

### Exhaust System

- Critical grade exhaust silencer
- Exhaust packages
- Industrial grade exhaust silencer
- Residential grade exhaust silencer

### Generator Set

- AC entrance box
- Batteries
- Battery charger
- Export box packaging
- UL 2200 Listed
- Main line circuit breaker
- PowerCommand Network Communication Module (NCM)
- QuietSite Stage 1 housing w/silencer
- QuietSite Stage 2 housing w/silencer
- Remote annunciator panel
- Spring isolators
- Weather protective enclosure with silencer
- 2 year prime power warranty
- 2 year standby warranty
- 5 year basic power warranty
- 10 year major components warranty

## Available Products and Services

A wide range of products and services is available to match your power generation system requirements. Cummins Onan products and services include:

Diesel and Spark-Ignited Generator Sets

Transfer Switches

Bypass Switches

Parallel Load Transfer Equipment

Digital Paralleling Switchgear

PowerCommand Network and Software

Distributor Application Support

Planned Maintenance Agreements

## Warranty

All components and subsystems are covered by an express limited one-year warranty. Other optional and extended factory warranties and local distributor maintenance agreements are available. Contact your distributor/dealer for more information.

## Certifications



**ISO9001** - This generator set was designed and manufactured in facilities certified to ISO9001.



**CSA** - This generator set is CSA certified to product class 4215-01 (pending).



**PTS** - The Prototype Test Support (PTS) program verifies the performance integrity of the generator set design. Products bearing the PTS symbol have been subjected to demanding tests in accordance to NFPA 110 Level 1 to verify the design integrity and performance under both normal and abnormal operating conditions including short circuit, endurance, temperature rise, torsional vibration, and transient response, including full load pickup.



**UL** - The generator set is available Listed to UL 2200, Stationary Engine Generator Assemblies (pending). The PowerCommand control is Listed to UL 508 - Category NITW7 for U.S. and Canadian usage.

## See your distributor for more information



**Cummins Power Generation**  
1400 73rd Avenue N.E.  
Minneapolis, MN 55432  
763.574.5000  
Fax: 763.574.5298  
[www.cumminspower.com](http://www.cumminspower.com)

Cummins and PowerCommand are registered trademarks of Cummins Inc.  
Detector and AmpSentry are trademarks of Cummins Inc.

**Important:** Backfeed to a utility system can cause electrocution and/or property damage. Do not connect generator sets to any building electrical system except through an approved device or after building main switch is open.