

Generator Set



125 kW, 156 kVA, Standby

113 kW, 141 kVA, Prime

DGEA 60 Hz Diesel Generator Set



Optional Features Shown

Description

This Cummins® Onan® DG-series diesel generator set is a fully integrated power generation system, providing optimum performance, reliability, and versatility for standby and prime power operation, in stationary or mobile applications.

A primary feature of the DG GenSet is strong motor starting capability and fast recovery from transient load changes. The DG torque matched system includes a heavy duty Cummins 4-cycle diesel engine, an AC alternator with high motor starting kVA capacity, and an electronic voltage regulator for precise regulation under steady-state or transient loads. The DG GenSet accepts 100% of the nameplate standby rating in one step, in compliance with NFPA 110 requirements.

The DG GenSet offers both user and environment friendly operation. The standard generator set control provides for local or automatic remote starting and stopping, operation, and automatic shutdown at fault detection. Controls may be upgraded to the Detector™, or to the PowerCommand® digital electronic control with AmpSentry™ protection. Exhaust emissions are certified to U.S. EPA Mobile Off Highway Tier I standards. Optional weather-protective housings and coolant heaters shield the generator set from extreme operating conditions. Environmental concerns are addressed by low exhaust emission engines, sound-attenuated housings, exhaust silencers, and dual-wall fuel tanks.

A wide range of options, accessories, and services are available, allowing configuration to your specific power generation needs.

Factory testing of each production unit is at rated load and power factor. This testing includes demonstration of rated power and single-step rated load pickup. Cummins Onan manufacturing facilities are registered to ISO9001 quality standards, emphasizing our commitment to high quality in the design, manufacture, and support of our products. DG generator sets are CSA certified and are available as UL2200 Listed.

All Cummins Onan brand power generation systems are backed by a comprehensive warranty program and supported by a worldwide network of 170 distributors and service branches to assist with warranty, service, parts, and planned maintenance support.

Features

- **UL Listed Generator Set** - The complete generator set assembly is available Listed to UL2200.
- **Low Exhaust Emissions** - Engine certified to U.S. EPA Mobile Off Highway Tier I standards.
- **Cummins Heavy-Duty Engine** - Rugged 4-cycle industrial diesel engine delivers reliable power, low emissions, and fast response to load changes.
- **Alternator** - Several alternator sizes offer selectable motor starting capability with low reactance 2/3 pitch windings, low waveform distortion with non-linear loads, fault clearing short-circuit capability, and class H insulation. The alternator electrical insulation system is UL1446 Recognized.
- **Control Systems** - The standard 2-wire remote control provides remote starting, operation, and protection features. Upgrade to the Detector™ Control with NFPA 110 compliance, or select the PowerCommand® advanced digital control for even greater capability and features. PowerCommand control is Listed to UL508.
- **Cooling Systems** - Standard cooling package provides reliable running at the rated power level, at up to 50°C ambient temperature.
- **Integral Vibration Isolation** - Robust skid base supports the engine, alternator, and radiator on isolators, minimizing transmitted vibration.
- **E-Coat Finish** - Dual electro-deposition paint system provides high resistance to scratching, corrosion, and fading.
- **Housings** - Optional weather-protective housings are available.
- **Fuel Tanks** - Dual wall sub-base fuel tanks and in-skid day tanks are also offered.
- **Certifications** - Generator sets are designed, manufactured, tested, and certified to relevant UL, NFPA, ISO, IEC, and CSA standards.
- **Warranty and Service** - Backed by a comprehensive warranty and worldwide distributor service network.

Generator Set

The general specifications in this document provide representative configuration details, but the outline drawing must be used for installation design.

Specifications – General

See outline drawing 500-3121 for installation design specifications.

Unit Width, in (mm)	40.0 (1016)
Unit Height, in (mm)	56.4 (1433)
Unit Length, in (mm)	104.8 (2662)
Unit Dry Weight, lb (kg)	3218 (1460)
Unit Wet Weight, lb (kg)	3313 (1503)
Rated Speed, rpm	1800
Voltage Regulation, No Load to Full Load	±1.0%
Random Voltage Variation	±1.0%
Frequency Regulation	5%
Random Frequency Variation	±0.5%
Radio Frequency Interference	Optional PMG excitation operates in compliance with BS800 and VDE level G and N. Addition of RFI protection kit allows operation per MIL-STD-461 and VDE level K.

Cooling	Standby	Prime
Fan Load, HP (kW)	7.9 (5.9)	7.9 (5.9)
Coolant Capacity with radiator, US Gal (L)	6.8 (25.7)	6.8 (26)
Coolant Flow Rate, Gal/min (L/min)	64.0 (242.2)	64.0 (242)
Heat Rejection To Coolant, Btu/min (MJ/min)	4700.0 (5.0)	4175.0 (4.4)
Heat Radiated To Room, Btu/min (MJ/min)	2661.0 (2.8)	2342.0 (2.5)
Maximum Coolant Friction Head, psi (kPa)	5.0 (34.5)	5.0 (34)
Maximum Coolant Static Head, psi (kPa)	60.0 (18.3)	60.0 (18.3)

Air	Standby	Prime
Combustion Air, scfm (m ³ /min)	452.0 (12.8)	442.0 (12.5)
Alternator Cooling Air, scfm (m ³ /min)	1308.0 (37.0)	1308.0 (37.0)
Radiator Cooling Air, scfm (m ³ /min)	6670.0 (188.8)	6670.0 (188.8)

Rating Definitions

Standby Rating based on: Applicable for supplying emergency power for the duration of normal power interruption. No sustained overload capability is available for this rating. (Equivalent to Fuel Stop Power in accordance with ISO3046, AS2789, DIN6271 and BS5514). Nominally rated.

Prime (Unlimited Running Time) Rating based on: Applicable for supplying power in lieu of commercially purchased power. Prime power is the maximum power available at a variable load for an unlimited number of hours. A 10% overload capability is available for limited time. (Equivalent to Prime Power in accordance with ISO8528 and Overload Power in accordance with ISO3046, AS2789, DIN6271, and BS5514). This rating is not applicable to all generator set models.

Base Load (Continuous) Rating based on: Applicable for supplying power continuously to a constant load up to the full output rating for unlimited hours. No sustained overload capability is available for this rating. Consult authorized distributor for rating. (Equivalent to Continuous Power in accordance with ISO8528, ISO3046, AS2789, DIN6271, and BS5514). This rating is not applicable to all generator set models.

Site Derating Factors

Engine power available up to 6585 ft (2007 m) at ambient temperatures up to 104°F (40°C). Above 6585 ft (2007 m) derate at 4% per 1000 ft (305 m), and 1% per 10°F (2% per 11°C) above 104°F (40°C).

Engine

Cummins heavy duty diesel engines use advanced combustion technology for reliable and stable power, low emissions, and fast response to sudden load changes. This generator set engine is certified to U.S. EPA Mobile Off Highway Tier I emissions standards. Mechanical governing is standard. Electronic governing is available for applications requiring constant (isochronous) frequency regulation such as Uninterruptible Power Supply systems, non-linear loads, or sensitive electronic loads. Optional coolant heaters are recommended for all emergency standby installations or for any application requiring fast load acceptance after start-up.

Specifications – Engine

Base Engine	Cummins Model 6CT8.3-G2, Turbocharged, diesel-fueled
Displacement in³ (L)	504.0 (8.3)
Overspeed Limit, rpm	2100 ±50
Regenerative Power, kW	22.00
Cylinder Block Configuration	Cast iron with replacable wet cylinder liners, In-line 6 cylinder
Cranking Current	550 amps at ambient temperature of 32°F (0°C)
Battery Charging Alternator	37 amps
Starting Voltage	12-volt, negative ground
Lube Oil Filter Types	Single spin-on canister-combination full flow with bypass
Standard Cooling System	104°F (40°C) ambient radiator

Power Output		Standby				Prime			
Gross Engine Power Output, bhp (kWm)		207.0 (154.4)				188.0 (140.2)			
BMEP at Rated Load, psi (kPa)		168.0 (1158.3)				152.0 (1048.0)			
Bore, in. (mm)		4.49 (114.0)				4.49 (114.0)			
Stroke, in. (mm)		5.32 (135.1)				5.32 (135.1)			
Piston Speed, ft/min (m/s)		1596.0 (8.1)				1596.0 (8.1)			
Compression Ratio		16.8:1				16.8:1			
Lube Oil Capacity, qt. (L)		25.2 (23.8)				25.2 (23.8)			
Fuel Flow									
Fuel Flow at Rated Load, US Gal/hr (L/hr)		54.0 (204.4)				54.0 (204.4)			
Maximum Inlet Restriction, in. Hg (mm Hg)		4 (102)				4 (102)			
Maximum Return Restriction, in. Hg (mm Hg)		10 (254)				10 (254)			
Air Cleaner									
Maximum Air Cleaner Restriction, in. H ₂ O (kPa)		25.0 (6.2)				25.0 (6.2)			
Exhaust									
Exhaust Flow at Rated Load, cfm (m ³ /min)		1221.0 (34.6)				980.0 (27.7)			
Exhaust Temperature, °F (°C)		1065 (574)				951 (511)			
Max Back Pressure, in. H ₂ O (kPa)		41.0 (10.2)				41.0 (10.2)			
Fuel System		Direct injection, number 2 diesel fuel, fuel filters; water separator; automatic electric fuel shutoff							
Fuel Consumption		Standby				Prime			
60 Hz Ratings, kW (kVA)		125 (156)				113 (141)			
	Load	1/4	1/2	3/4	Full	1/4	1/2	3/4	Full
	US Gal/hr	3.3	5.4	7.5	9.9	3.1	4.9	6.9	8.9
	L/hr	12	20	28	37	12	19	26	34

Alternator

Several alternators are available for application flexibility, based on the required motor starting kVA and other requirements. Larger alternator sizes have lower temperature rise for longer life of the alternator insulation system. In addition, larger alternator sizes can provide a cost-effective use of engine power in across-the-line motor starting applications and can be used to reduce voltage waveform distortion caused by non-linear loads.

These single-bearing alternators couple directly to the engine flywheel with flexible discs, for drivetrain reliability and durability. No gear reducers or speed changers are used. Two-thirds pitch windings eliminate third-order harmonic content of the AC voltage waveform and provide the standardization desired for paralleling of generator sets. The standard excitation system is a self (shunt) excited system with the voltage regulator powered directly from the generator set output.

Alternator Application Notes

Separately Excited Permanent Magnet Generator (PMG) System - This option uses an integral PMG to supply power to the voltage regulator. A PMG system generally has better motor starting performance, lower voltage dip upon load application, and better immunity from problems with harmonics in the main alternator output induced by non-linear loads. This option is recommended for use in applications that have large transient loads, sensitive electronic loads (especially UPS applications), harmonic content, or that require sustained short-circuit current (sustained 3-phase short circuit current at approximately 3 times rated for 10 seconds).

Alternator Sizes - On any given model, various alternator sizes are available to meet individual application needs. Alternator sizes are differentiated by maximum winding temperature rise, at the generator set standby or prime rating, when operated in a 40°C ambient environment. Available temperature rises range from 80°C to 150°C. Not all temperature rise selections are available on all models. Lower temperature rise is accomplished using larger alternators at lower current density. Lower temperature rise alternators have higher motor starting kVA, lower voltage dip upon load application, and they are generally recommended to limit voltage distortion and heating due to harmonics induced by non-linear loads.

Alternator Space Heater - is available and recommended, to inhibit condensation.

Available Output Voltages

<u>Three Phase Reconnectable</u>	<u>Single Phase Non-Reconnectable</u>	<u>Three Phase Non-Reconnectable</u>
[] 120/208	[] 120/240	[] 220/380
[] 127/220		[] 347/600
[] 139/240		
[] 120/240		
[] 240/416		
[] 254/440		
[] 277/480		

Specifications – Alternator

Design	Brushless, 4-pole, drip-proof revolving field
Stator	2/3 pitch
Rotor	Direct-coupled by flexible disc
Insulation System	Class H per NEMA MG1-1.65
Standard Temperature Rise	150°C standby
Exciter Type	Shunt
Phase Rotation	A (U), B (V), C (W)
Alternator Cooling	Direct-drive centrifugal blower
AC Waveform Total Harmonic Distortion	<5% total no load to full linear load <3% for any single harmonic
Telephone Influence Factor (TIF)	<50 per NEMA MG1-22.43.
Telephone Harmonic Factor (THF)	<3

Three Phase Table ¹		105° C	105° C	105° C	105° C	125° C	125° C	125° C	125° C	150° C	150° C	150° C	
Feature Code		B418	B415	B268	B304	B417	B414	B267	B303	B416	B413	B419	
Alternator Data Sheet Number		209	209	211	208	208	208	211	208	208	208	208	
Voltage Ranges		110/190 Thru 120/208 220/380 Thru 240/416	120/208 Thru 139/240 240/416 Thru 277/480	120/208 Thru 139/240 240/416 Thru 277/480	347/600	110/190 Thru 120/208 220/380 Thru 240/416	120/208 Thru 139/240 240/416 Thru 277/480	120/208 Thru 139/240 240/416 Thru 277/480	347/600	110/190 Thru 120/208 220/380 Thru 240/416	120/208 Thru 139/240 240/416 Thru 277/480	347/600	
Surge kW		138	137	139	137	137	136	139	137	137	136	137	
Motor Starting kVA (at 90% sustained voltage)	Shunt	516	516	672	422	422	422	672	422	422	422	422	
	PMG	607	607	791	497	497	497	791	497	497	497	497	
Full Load Current - Amps at Standby Rating		$\frac{120/208}{434}$	$\frac{127/220}{410}$	$\frac{139/240}{376}$	$\frac{220/380}{237}$	$\frac{240/416}{217}$	$\frac{254/440}{205}$	$\frac{277/480}{188}$	$\frac{347/600}{150}$				

Notes:

1. Single phase power can be taken from a three phase generator set at up to 2/3 set rated 3-phase kW at 1.0 power factor. Also see Note 2 below.

Single Phase Table		105° C	105° C	105° C	105° C	125° C	125° C	125° C	125° C				
Feature Code		B418	B415	B274	B268	B417	B414	B273	B267				
Alternator Data Sheet Number		209	209	210	211	208	208	209	211				
Voltage Ranges		120/240 ¹	120/240 ¹	120/240 ²	120/240 ²	120/240 ¹	120/240 ¹	120/240 ²	120/240 ²				
Surge kW		134	134	137	136	134	134	136	136				
Motor Starting kVA (at 90% sustained voltage)	Shunt	305	305	330	395	250	250	305	395				
	PMG	360	360	385	465	290	290	360	465				
Full Load Current - Amps at Standby Rating		$\frac{120/240^1}{347}$	$\frac{120/240^2}{521}$										

Notes:

1. The broad range alternators can supply single phase output up to 2/3 set rated 3-phase kW at 1.0 power factor.
2. The extended stack (full single phase output) and 4 lead alternators can supply single phase output up to full set rated 3-phase kW at 1.0 power factor.

Control System



Optional Features Shown

Standard - 2 Wire Remote Control System	
<ul style="list-style-type: none"> Automatic remote starting Control components designed to withstand the vibration levels typical in generator sets Controls generator set starting and shutdown 	
Standard Control Description	
<ul style="list-style-type: none"> Remote starting, 12 V, 2 wire Run-Off-Auto switch 	<ul style="list-style-type: none"> Crank timer Fault reset button
Standard Features	Optional Features
<ul style="list-style-type: none"> Field circuit breaker High temperature shutdown Low oil pressure shutdown Overcrank shutdown Overspeed shutdown Running time meter 	<ul style="list-style-type: none"> AC meter package (same as Detector) Oil pressure gauge (engine mounted) Water temperature gauge (radiator mounted)



Optional Features Shown

Optional - Detector® Control System	
<ul style="list-style-type: none"> Automatic remote starting Control components designed to withstand the vibration levels typical in generator sets Controls generator set starting and shutdown 	
Standard Detector 12 Light (NFPA110) Control Description	
<ul style="list-style-type: none"> 12 light engine monitor (NFPA110 level) Common alarm contact Coolant temperature gauge Cycle cranking control DC voltmeter Field circuit breaker Individual 1/2 A relay signals 	<ul style="list-style-type: none"> Lamp test switch Oil pressure gauge Remote starting, 12 V, 2 wire Reset switch Run-Off-Auto switch Running time meter

Standard Features	Optional Features
<ul style="list-style-type: none"> 5% voltage adjust rheostat AC ammeter (dual scale) AC voltmeter (dual scale) Dual scale frequency/engine RPM meter High coolant temp shutdown (red light) Low coolant temperature (yellow light) Low fuel (yellow light) Low oil pressure shutdown (red light) 	<ul style="list-style-type: none"> Overcrank shutdown (red light) Overspeed shutdown (red light) Pre-alarm high coolant temp (yellow light) Pre-alarm low oil pressure (yellow light) Run indicator (green light) Two customer selected faults (red light) Voltmeter/Ammeter phase selector
	<ul style="list-style-type: none"> Audible alarm CSA282 Emergency stop Low battery voltage warning Remote fault signal package Speed adjust rheostat Time delay start/stop



Optional Features Shown

Optional - PowerCommand® Control with AmpSentry™ Protection	
<ul style="list-style-type: none"> AmpSentry Protection guards the electrical integrity of the alternator and power system from the effects of overcurrent, over/under voltage, under frequency and overload conditions Control components are designed to withstand the vibration levels typical in generator sets Integrated automatic voltage regulator and engine speed governor 	
Standard Control Description	
<ul style="list-style-type: none"> Analog % of current meter (amps) Analog % of load meter (kW) Analog AC frequency meter Analog AC voltage meter Cycle cranking control Digital display panel Emergency stop switch Idle mode control Menu switch 	<ul style="list-style-type: none"> Panel backlighting Remote starting, 12 V, 2 wire Reset switch Run-Off-Auto switch Sealed front panel, gasketed door Self diagnostics Separate customer interconnection box Voltmeter/Ammeter phase selector switch

Standard Protection Functions	Standard Performance Data
<p>Warnings</p> <ul style="list-style-type: none"> High coolant temperature High DC voltage Low coolant temperature Low DC voltage Low fuel-day tank Low oil pressure Oil pressure sender fault Overcurrent Overload load shed contacts Temperature sender fault Up to four customer fault inputs Weak battery 	<p>Shutdowns</p> <ul style="list-style-type: none"> Emergency stop Fail to crank High AC voltage High coolant temperature High AC voltage Low AC voltage Low coolant level (option for alarm only) Low oil pressure Magnetic pickup failure Overcrank Overcurrent Overspeed Short circuit Underfrequency <p>AC Alternator</p> <ul style="list-style-type: none"> Current by phase Kilowatts Kilowatt hours Power factor Voltage line to line Voltage line to neutral <p>Engine Data</p> <ul style="list-style-type: none"> Battery voltage Coolant temperature Engine running hours Engine starts counter Oil pressure Oil temperature RPM

Generator Set Options

Engine	Control Panel	Generator Set
<input type="checkbox"/> 120/240 V, 1000 W coolant heaters	<input type="checkbox"/> Detector 12 control	<input type="checkbox"/> AC entrance box
	<input type="checkbox"/> Engine gauges	<input type="checkbox"/> Batteries
Fuel System	<input type="checkbox"/> Low coolant level warning/shutdown	<input type="checkbox"/> Battery charger
<input type="checkbox"/> 125 Gal (473 L) single wall sub-base tank		<input type="checkbox"/> UL2200 Listed
Alternator		<input type="checkbox"/> Main line circuit breaker
<input type="checkbox"/> 120/240 V, 100 W anti-condensation heater		<input type="checkbox"/> Remote annunciator panel
<input type="checkbox"/> PMG excitation		<input type="checkbox"/> Spring isolators
<input type="checkbox"/> Single phase		<input type="checkbox"/> Weather protective enclosure with silencer
		<input type="checkbox"/> 2 year standby warranty
		<input type="checkbox"/> 5 year basic power warranty

Available Products and Services

A wide range of products and services is available to match your power generation system requirements. Cummins Onan products and services include:

- Diesel and Spark-Ignited Generator Sets
- Transfer Switches
- Bypass Switches
- Parallel Load Transfer Equipment
- Digital Paralleling Switchgear
- PowerCommand Network and Software
- Distributor Application Support
- Planned Maintenance Agreements

Warranty

All components and subsystems are covered by an express limited one-year warranty. Other optional and extended factory warranties and local distributor maintenance agreements are available.

Other available warranties include: 2-year prime power, 2-year standby, 5-year basic power, 5-year comprehensive power and 10-year major component. The 2-year prime power and the 10-year major component warranties are available in North America only.

Certifications



UL - The generator set is available Listed to UL2200, Stationary Engine Generator Assemblies.

ISO9001 - This generator set was designed and manufactured in facilities certified to ISO9001.

CSA - This generator set is CSA certified to product class 4215-01.

NFPA - The Prototype Test Support (PTS) program verifies the performance integrity of the generator set design. Cummins Onan products bearing the PTS symbol meet the prototype test requirements of NFPA 110 for Level 1 systems. A complete representative prototype generator set has been subjected to a number of demanding tests to verify the design integrity and performance under both normal and abnormal operating conditions per the requirements of NFPA 110 for Level 1 systems. Tests include short circuit, endurance, temperature rise, torsional vibration, and transient response, including full load pickup in one step.

UL - The PowerCommand control is Listed UL508 - Category NITW7 for U.S. and Canadian usage.

See your distributor for more information



Onan Corporation
1400 73rd Avenue N.E.
Minneapolis, MN 55432
612.574.5000
Fax: 612.574.5298

Onan and PowerCommand are registered trademarks of Onan Corporation.
Cummins is a registered trademark of Cummins Engine Company.
Detector and AmpSentry are trademarks of Onan Corporation.
Windows is a registered trademark of Microsoft.

Important: Backfeed to a utility system can cause electrocution and/or property damage. Do not connect to any building's electrical system except through an approved device or after building main switch is open.