



Load Bank Test Report

Engine Make/ Model: F2CE9685A
 Engine Spec/ Serial: E002-029729 8.7L
 Unit Make/ Model: 15046080200
 Unit Spec/ Serial: 7872791

Voltage: 120/208
 Amperage: 639
 Kilowatts: 230
 Power Factor 1

	Warm Up	Start	15 Min.	30 Min.	45 Min.	1 Hour	Cool Down
Eng Hours	531.6	531.6	531.8	532.1	532.3	532.6	532.6
Hertz/Cycles	60	60	60	60	60	60	60
Voltage PH1	208	208	208	208	208	208	208
PH2	208	208	208	208	208	208	208
PH3	208	208	208	208	208	208	208
Amperage PH1	0	646	646	646	646	646	0
PH2	0	648	649	649	648	647	0
PH3	0	649	649	646	649	649	0
Kilowatts	0	233	234	232	233	232	0
Oil Pressure	93	90	85	85	85	85	0
Coolant Temperature	60	117°F	186°F	186°F	186°F	185°F	180°F
DC Voltage	28.1	28.1	28.1	28.1	28.1	28.1	28.1
Ambient Temperature	61	62°F	62°F	62°F	62°F	62°F	62°F

Technician Signature Jonathan Mueller

Test Date 3/11/2024



3/11/24

CSDG #4443

Generator Check list

Inspection Description

- Yes No NA Check coolant level and record freeze protection: -25
- Yes No NA Visual inspection of radiator: Good
- Yes No NA Visual inspection of radiator hoses: Good
- Yes No NA Check condition of coolant hoses: Good
- Yes No NA Check condition of fuel hoses: Good
- Yes No NA Check condition of engine belts: Good
- Yes No NA Batteries and QTY: 2 Duracell SLI3PPA
- Yes No NA Battery install date if applicable: 3/16/2020
- Yes No NA Genset has battery charger: 12V 10A
- Yes No NA Genset has coolant heater: 2000W, 240V, 084918N
- Yes No NA Check engine oil level: Good
- Yes No NA Engine oil filters last changed date and HRS: 3/8/22 175hrs
- Yes No NA Inspect exhaust system for cracks / leaks: Good
- Yes No NA Check rain cap for proper operation: Good
- Yes No NA Generator end is 12 lead reconnectable:
- Yes No NA Generator end has PMG permanent magnet generator:
- Yes No NA Electronic Engine: